

PRODUCT SPECIFICATION

StreamLEDTM

Flexible LED Wall Washer Strip

Model: SL-18W-24



Product Specification LED WALL WASHER



Product Introduction

- Thermoplastic Polyurethane construction is resistant to yellowing, high temperature, corrosion, mild acid & alkali, with impressive flexibility.
- Replaces the traditional hard wall washer or LED strip.
- Compact, light weight, flexible and easy to install.
- Beam angles (30°, 45°, 60°, 20°x45°) are available for different applications.
















Product Dimensions



Maximum length for per roll 5mt.



Application








CORELLI LIGHTING CONCEPTS PTY LTD | 68 LAMBECK DVE, TULLAMARINEVIC, 3043 | TEL: 03 9338 9337 | FAX: 03 9338 9937 | MOB: 0419 586 561 | WEB: WWW.CORELLI.COM.AU | EMAIL: INFO@CORELLI.COM.AU

Product Specification LED WALL WASHER

Bending Capacity



Accessories





3M Tape

Plastic Holding Clips





Stainless Steel Mounting Clips

Aluminum Profile

Parameters


Model No.	SL-18W-24
Input Voltage	24V
Power	18W/m
CRI(Ra)	>90
Beam Angle	30°/45°/60°/20°x45°

LEDs/m	48LEDs
Operating Hours	50000hrs
Operating Temperature	-25°C ~ +45°C
Cuttable Length(mm)	125mm
IP Rating	IP67

ССТ	2700K ±100K	3000K ±100K	4000K ±200K	6500K ±200K
Lumen/m	1851LM	1915LM	2167LM	1949LM

Also available in RGB (6.2W/m-42 LEDs/m), RGW (8W/m-42 LEDs/m) & RGW-DMX (8.5W/m-36LEDs/m)


Light Distribution





CORELLI LIGHTING CONCEPTS PTY LTD | 68 LAMBECK DVE, TULLAMARINEVIC. 3043 | TEL: 03 9338 9337 | FAX: 03 9338 9937 | MOB: 0419 586 561 | WEB: WWW.CORELLI.COM.AU | EMAIL: INFO@CORELLI.COM.AU


Product Specification LED WALL WASHER

Positioning / Effect






















































Product Specification LED WALL WASHER


Wiring Diagram




Correct Method



During the installation process, the streamLED must be removed from the reel gently and kept as straight as possible to allow the strip to gently uncurl.




Avoid over bending the streamLED the installation process.




When the streamLED hangs of the corner during the installation process, the strip must be kept facing upwards, maintaining a certain bending arc, $\Phi \ge 150 \text{mm}$ to avoid damage.


Incorrect Method



Do not twist the streamLED during the installation process.



Do not fold the streamLED in half or bend it at a sharp angle during the installation.



When the streamLED hangs the corner during the installation process, the strip must not fold or it will be damaged.

CORELLI LIGHTING CONCEPTS PTY LTD | 68 LAMBECK DVE, TULLAMARINE VIC. 3043 | TEL: 03 9338 9337 | FAX: 03 9338 9937 | MOB: 0419 586 561 | WEB: WWW.CORELLI.COM.AU | EMAIL: INFO@CORELLI.COM.AU